



*Knowledge Resource & Relay Centre (KRRC)*

School: SoET-REV. C-SCHEME Branch: EXTC SEM: VIII

To,  
Exam Controller,  
AIKTC, New Panvel.

Dear Sir/Madam,

Received with thanks the following **Semester/Unit Test-I/Unit Test-II (Reg./ATKT)** question papers from your exam cell:

Sr. No.	Subject Name	Subject Code	Format		No. of Copies
			SC	HC	
1	RF Design	ECC801		✓	
2	Wireless Networks	ECC802		✓	
3	Department Level Optional Course IV	ECC803		✓	
4	Institute Level Optional Course II Digital Business Management	ETE80X		✓	
5					
6					

Note: SC – Softcopy, HC - Hardcopy

(Shaheen Ansari)  
Librarian, AIKTC

Q.P code :- 10013050

Paper / Subject Code: 52951 / RF Design

Sem - VIII - CBCR - KT ET

Time: 3 hour

Max Marks: 80

Note: 1. Each question carries 20 marks

2: Question no 1 is compulsory

3: Solve any 3 out of remaining

4: Assume suitable data wherever required.

- Q1. Solve any four 20
- A) What is the stability in Amplifier? Why the stability parameter  $\mu$  is required though  $\Delta$  and  $K$  are there?
- B) Explain the power amplifier performance parameters
- C) Explain Richard's Transformation
- D) Explain working principal of Image Reject Mixer.
- E) Draw one port oscillator circuit. Find value of  $R_L$  which maximizes oscillator power.
- Q2 A) Design a low pass filter whose input and output are matched to a  $50\Omega$  impedance with cut off frequency of 3 GHz, equi-ripple of 0.5 dB and rejection of at least 40 dB at approximately twice the cut-off frequency. 10
- B) Design an amplifier for a power gain of 15 dB at a frequency of 3 GHz, if the selected bipolar transistor with  $V_{CE} = 4V$  and  $I_c = 5 mA$  has following S parameters. 10  
 $S_{11} = 0.7\angle -155^\circ$ ,  $S_{12} = 0$ ,  $S_{21} = 4\angle 180^\circ$ ,  $S_{22} = 0.51\angle -20^\circ$
- Q3 A) An amplifier is having gain of 11 dB at 4 GHz. Plot constant gain circles for  $G_s = 2$  dB and 3 dB and  $G_L = 0$  dB and 1dB using following S parameters. 10  
 $S_{11} = 0.75\angle -120^\circ$ ,  $S_{12} = 0$ ,  $S_{21} = 2.5\angle 80^\circ$ ,  $S_{22} = 0.6\angle -70^\circ$
- B) An  $N = 3$  Chebyshev band pass filter is to be designed with 3 dB pass band ripple. 10  
The centre frequency is at 2.4 GHz and the filter has to meet bandwidth requirement of 20%. The filter has to be inserted into  $50\Omega$  characteristics line impedance. Find the inductive and capacitive elements.
- Q4 A) What is the indirect frequency synthesis? What is the effect of choice of reference frequency ( $f_r$ ) on the performance of frequency synthesizer? 10
- B) Explain in detail phase noise and its effect on oscillator design. 10
- Q5. A) Explain LISN in detail and how it is useful in conducting EMI tests. 10
- B) What is shielding? Explain shielding effectiveness. 10
- Q6. A) Explain variable modulus along with its expression. 10
- B) What is ESD? Model ESD waveform and explain equivalent circuit model for ESD. 10

TABLE 8.4 Element Values for Equal-Ripple Low-Pass Filter Prototypes ( $g_0 = 1, \omega_c = 1, N = 1$  to 10, 0.5 dB and 3.0 dB ripple)

N	0.5 dB Ripple										
	$g_1$	$g_2$	$g_3$	$g_4$	$g_5$	$g_6$	$g_7$	$g_8$	$g_9$	$g_{10}$	$g_{11}$
1	0.6986	1.0000									
2	1.4029	0.7071	1.9841								
3	1.5963	1.0967	1.5963	1.0000							
4	1.6703	1.1926	2.3661	0.8419	1.9841						
5	1.7058	1.2296	2.5408	1.2296	1.7058	1.0000					
6	1.7254	1.2479	2.6064	1.3137	2.4758	0.8696	1.9841				
7	1.7372	1.2583	2.6381	1.3444	2.6381	1.2583	1.7372	1.0000			
8	1.7451	1.2647	2.6564	1.3590	2.6964	1.3389	2.5093	0.8796	1.9841		
9	1.7504	1.2690	2.6678	1.3673	2.7239	1.3673	2.6678	1.2690	1.7504	1.0000	
10	1.7543	1.2721	2.6754	1.3725	2.7392	1.3806	2.7231	1.3485	2.5239	0.8842	1.9841

  

N	3.0 dB Ripple										
	$g_1$	$g_2$	$g_3$	$g_4$	$g_5$	$g_6$	$g_7$	$g_8$	$g_9$	$g_{10}$	$g_{11}$
1	1.9953	1.0000									
2	3.1013	0.5339	5.8095								
3	3.3487	0.7117	3.3487	1.0000							
4	3.4389	0.7483	4.3471	0.5920	5.8095						
5	3.4817	0.7618	4.5381	0.7618	3.4817	1.0000					
6	3.5045	0.7685	4.6061	0.7929	4.4641	0.6033	5.8095				
7	3.5182	0.7723	4.6386	0.8039	4.6386	0.7723	3.5182	1.0000			
8	3.5277	0.7745	4.6575	0.8089	4.6990	0.8018	4.4990	0.6073	5.8095		
9	3.5340	0.7760	4.6692	0.8118	4.7272	0.8118	4.6692	0.7760	3.5340	1.0000	
10	3.5384	0.7771	4.6768	0.8136	4.7425	0.8164	4.7260	0.8051	4.5142	0.6091	5.8095

Source: Reprinted from G. L. Matthaei, L. Young, and E. M. T. Jones, *Microwave Filters, Impedance-Matching Networks, and Coupling Structures*, Artech House, Dedham, Mass., 1980, with permission.

ET - Sem - VIII - CBCS - KT

Duration: 3hrs

[Max Marks:80]

- N.B. : (1) Question No 1 is Compulsory.  
(2) Attempt any three questions out of the remaining five.  
(3) All questions carry equal marks.  
(4) Assume suitable data, if required and state it clearly.

- 1 Attempt any FOUR [20]  
a Compare and contrast digital economy and physical economy  
b What are the types of E-marketplaces? Explain?  
c What are the advantages of E-Commerce?  
d Explain how knowledge management differs from information management.  
e What is Firewall? How Firewall can be configured?
- 2 a What is business plan? Why is it required in any business organization? [10]  
b Explain different types of E Business? [10]
- 3 a Explain Digital Signature and PKI [10]  
b Explain Analysis of Company's Internal and External environment [10]
- 4 a Describe different security attacks. Also explain any one encryption and decryption technique. [10]  
b Explain Firewall as Security Control [10]
- 5 a What is Information System? Explain its Components? [10]  
b Explain the risk and list the steps to manage the risk in the e-business [10]
- 6 a Discuss various Legal, Ethics and Societal impacts of E-commerce [10]  
b What is business plan? Why it is required in any business organization? [10]

\*\*\*\*\*